

# EN530.603 Applied Optimal Control

## Homework #2

September 21, 2018

Due: September 26, 2018 (before class)

Prof: Marin Kobilarov

1. Find the curve  $x^*$  that minimizes

$$J(x) = \int_0^1 \left( \frac{1}{2} \dot{x}^2(t) + 3x(t)\dot{x}(t) + 2x^2(t) + 3x(t) \right) dt$$

and passes through the points  $x(0) = 0$  and  $x(1) = 4$ .

2. Find the extremals for

$$J(x) = \int_0^{t_f} [\dot{x}_1^2(t) + \dot{x}_2^2(t) + 3x_1(t)x_2(t)] dt,$$

with

a)  $x_1(0) = 0$ ,  $x_2(0) = 0$ ,  $t_f = 1$ ,  $x_1(t_f)$  free,  $x_2(t_f) = 1$ .

b)  $x_1(0) = 0$ ,  $x_2(0) = 0$ ,  $t_f$  free,  $x(t_f)$  must lie on the surface

$$x_1(t) + 3x_2(t) + 5t = 15$$

Note: the last constraint is of the general form  $\psi(x(t_f), t_f) = 0$ . See last section in Lecture#4 posted on the website for details.

3. (Kirk 4-5.) Let  $\eta$  be a continuously differentiable function of time  $t$  that is arbitrary on the interval  $[t_0, t_f]$  except at the end-points where  $\eta(t_0) = \eta(t_f) = 0$ . If  $\epsilon$  is an arbitrary real parameter, then  $x^* + \epsilon\eta$  represents a family of curves. Evaluating the functional

$$J(x) = \int_{t_0}^{t_f} g(x(t), \dot{x}(t), t) dt$$

on  $x = x^* + \epsilon\eta$  makes  $J$  a function of  $\epsilon$ , and if  $x^*$  is an extremal this function must have a relative extremum at  $\epsilon = 0$ .

Show that the Euler-Lagrange equations can be equivalently obtained from the necessary condition

$$\left. \frac{dJ(x^* + \epsilon\eta)}{d\epsilon} \right|_{\epsilon=0} = 0.$$

Note: upload your code using the File Upload link on the website. In addition attach a printout of the code and plots to your homework solutions.